# AD A 1 0 5 8 6 4

### LEVEL



## NAVAL POSTGRADUATE SCHOOL Monterey, California





### **THESIS**

CERENKOV RADIATION PRODUCED BY 100 MeV ELECTRONS

by

David Earl McLaughlin
June 1981

Thesis Advisor:

Fred R. Buskirk

Approved for public release; distribution unlimited

MIL FILE, COP

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Date Entered) READ INSTRUCTIONS BEFORE COMPLETING FORM REPORT DOCUMENTATION PAGE AECIRIENT'S CATALOG NUMBER REPORT NUMBER 2. GOVT ACCESSION NO .05 864 4- 7175 ( me Sustille) SA TYPE OF REPORT & PERIOD COVERED Master's Thesis, June Cerenkov Radiation Produced by 100 MeV 1981 Electrons, 4. PERFORMING ORG. REPORT NUMBER 7. AUTHORIAL .. S. CONTRACT OR GRANT NUMBER(4) David Earl McLaughlin 9. PERFORMING ORGANIZATION NAME AND ADDRESS 18. PROGRAM ELEMENT, PROJECT, AREA & WORK UNIT NUMBERS Naval Postgraduate School Monterey, California 93940 11. CONTROLLING OFFICE NAME AND ADDRESS 13 - REPORT DATE Jun**-19**81 Naval Postgraduate School Monterey, California 93940 13. NUMBER OF PAGES 48 pages 14. MONITORING AGENCY NAME & ADDRESS(II different from Controlling Office) 18. SECURITY CLASS. (of this report) Unclassified 154, DECLASSIFICATION/DOWNGRADING 16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited 17. DISTRIBUTION STATEMENT (of the abstract entered in Black 20, if different from Report) IS. SUPPLEMENTARY NOTES 19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Stimulated Cerenkov radiation, superluminal, LINAC beam monitor. 20. ABSTRACT (Continue on reverse side if necessary and identify by block mambet) It is proposed that electromagnetic radiation of a specified frequency can be produced as a result of stimulated Cerenkov radiation in a dielectric resonator excited by a superluminal electron beam. The frequency generated is a function of three

DD FORM 1473 (Page 1)

EDITION OF 1 NOV 55 18 OBSOLETE 5/N 0102-014-6601 | SECURITY CLASSIFICATION OF THIS PAGE (Man Date Shiere

physical parameters. They are the electron energy, the thickness of the dielectric resonator and its index of refraction. This work provides a theoretical derivation for predicting the frequency

### UNCLASSIFIED

SOCUMETY CLASSIFICATION OF THIS PAGE/When Rote Bottom

Item 20 (contd)

of stimulated Cerenkov radiation in a dielectric slab. The first experimental results using extremely relativistic electrons are reported, and the problems encountered are outlined with some suggestions for improvements. The results of this validation show that the observed frequency differs from the predicted frequency by less than 1.5%. Incidental to the conduct of this experiment, ordinary Cerenkov radiation in the usual cone was observed in air at microwave frequencies. A possible application of the stimulated Cerenkov process as an electron beam monitor is briefly discussed.

### Appoved for public release; distribution unlimited

Cerenkov Radiation Produced by 100 MeV Electrons

by

David Earl McLaughlin Lieutenant Commander, United States Navy B.S.M.E., Michigan State University, 1969

Submitted in partial fulfillment of the requirements for the degree of

MASTER OF SCIENCE IN PHYSICS

from the

NAVAL POSTGRADUATE SCHOOL June 1981 Accession For

NIIS CRA&I
DTIC TAB
Uninnounced
Justification

Ry
Distribution/
Availability Codes
Avail and/or
Dist
Special

Author:	David E. M. Layhlin
Approved by:	Fred R Bushick
inpproved by .	Thesis Advisor
	AN Oyer
	Second Reader
	Ar Over
	Chairman, Department of Chemistry and Physics
	William M. Idles
	Dean of Science and Engineering

### **ABSTRACT**

It is proposed that electromagnetic radiation of a specified frequency can be produced as a result of stimulated Cerenkov radiation in a dielectric resonator excited by a superluminal electron beam. The frequency generated is a function of three physical parameters. They are the electron energy, the thickness of the dielectric resonator and its index of refraction. This work provides a theoretical derivation for predicting the frequency of stimulated Cerenkov radiation in a dielectric slab. The first experimental results using extremely relativistic electrons are reported, and the problems encountered are outlined with some suggestions for improvements. The results of this validation show that the observed frequency differs from the predicted frequency by less than 1.5%. Incidental to the conduct of this experiment, ordinary Cerenkov radiation in the usual cone was observed in air at microwave frequencies. A possible application of the stimulated Cerenkov process as an electron beam monitor is briefly discussed.

### TABLE OF CONTENTS

I.	INTRODUCTION	-
II.	THEORY	11
III.	EXPERIMENTAL EQUIPMENT AND PROCEDURE	25
IV.	DISCUSSION AND CONCLUSIONS	38
APPENI	DIX A: NPS LINAC OPERATING CHARACTERISTICS	4]
APPENI	DIX B: TI-59 PROGRAM LISTING AND EXPLANATION	42
LIST (	OF REFERENCES	47
TNTTI	AL DISTRIBUTION LIST	4 8

### LIST OF TABLES

I.	Thicknesses	of	Polyethelyne	for	Modes	0,1,2	25
TT.	Frequencies	Obs	served				36

### LIST OF FIGURES

1.	Coordinate System	-12
2.	Graphical Solution	-17
3.	Geometric Relationships	-21
4.	Dielectric Resonator	-27
5.	Air Cerenkov Experimental Setup	-29
6.	Vacuum Chamber	-31
7.	E-Field in the Dielectric	-34
8.	Vertical Conductor in Dielectric	_ 35

### **ACKNOWLEDGEMENTS**

The author wishes to express his gratitude to his thesis advisor, Professor Fred R. Buskirk, for his instruction, guidance and assistance in all phases of this project.

Thanks are also extended to Professor J. Knorr of the Naval Postgraduate School's Electrical Engineering Department for providing equipment and for his many helpful suggestions in the course of this work, and to Professor John E. Walsh of Dartmouth College for his encouragement.

The assistance of Mr. Don Snyder in the fabrication of the experimental setup and in the day-to-day operation and maintenance of the NPS LINAC is greatly appreciated.

Finally, the author wishes to thank his wife, Catherine, for her understanding, patience and support throughout this work and for her assistance in composition and proofreading.

### I. INTRODUCTION

Cerenkov radiation, the radiation which is generated by a charged particle moving at superluminal velocity in a medium has been considered as a possible radiation source for many years. Additionally, Cerenkov radiation has been used as a charged particle detector which will selectively detect only charged particles exceeding the speed of light in the medium through which they are traveling. This detection is dependent upon only the velocity of the particle and the index of refraction of the medium. The detector is a simple photocell and as such does not distinguish between frequencies within its band of operability. Recently, Professor John E. Walsh [Ref. 1] reported successful generation of Cerenkov radiation using relativistic electrons and a dielectric resonator in the form of a cylindrical anulus. The import of Walsh's work is that the frequency of the radiation generated in the dielectric is a function only of the energy of the electrons, the thickness of the dielectric, and the index of refraction of the dielectric. Since these quantities are material parameters, it would appear that radiation of any desired frequency could be obtained by selecting the proper set of parameters.

The intent of this experiment is to extend Walsh's work, using a different geometry for the dielectric resonator and

much higher electron energies. Professor Walsh conducted his experiments at 300 KeV in contrast to the present experiment, which uses electron energies in the 10-100 MeV range, an increase of 1.5 to 2 orders of magnitude. In this experiment, radiation in the X band was selected for ease of measurement and analysis, with a view to extending the work into the IR range.

### II. THEORY

Consider a dielectric slab with a coordinate system as shown in Figure 1. The dielectric has thickness h in the z direction and is unbounded in the x and y directions. There is a dielectric-conductor interface at z=0 which lies in the x-y plane. The dielectric slab has permittivity  $\epsilon$  and permeability  $\mu_0$  while these quantities are  $\epsilon_0$  and  $\mu_0$ , respectively, in vacuum.

Starting with Maxwell's equations and following the usual procedure, it can be shown that the longitudinal components,  $E_{_{\rm X}}$  or  $H_{_{\rm X}}$ , satisfy a wave equation and the modes can be divided into TE or TM modes. The general expressions for the transverse components of the wave equation solution are:


$$H_{y} = \frac{i\omega\varepsilon}{\omega^{2}\mu\varepsilon - k^{2}} \frac{\partial E_{x}}{\partial z} - \frac{ik}{\omega^{2}\mu\varepsilon - k^{2}} \frac{\partial H_{x}}{\partial y}$$
(1)

$$F_{z} = \frac{-ik}{\omega^{2} \mu \epsilon - k^{2}} \frac{\partial E_{x}}{\partial z} + \frac{i\omega \mu}{\omega^{2} \mu \epsilon - k^{2}} \frac{\partial H_{x}}{\partial y}$$
 (2)

$$E_{y} = \frac{-i\omega\mu}{\omega^{2}\mu\varepsilon - k^{2}} \frac{\partial H_{x}}{\partial z} - \frac{ik}{\omega^{2}\mu\varepsilon - k^{2}} \frac{\partial E_{x}}{\partial y}$$
(3)

$$H_{z} = \frac{-ik}{\omega^{2}\mu\varepsilon - k^{2}} \frac{\partial H_{x}}{\partial z} - \frac{i\omega\varepsilon}{\omega^{2}\mu\varepsilon - k^{2}} \frac{\partial E_{x}}{\partial y}$$
 (4)

The intent of this experiment is to take energy from a beam of electrons in the vacuum just above the dielectric slab



COORDINATE SYSTEM

FIGURE 1.

and give this energy to an EM wave in the slab and in the vacuum above the slab. This energy transfer requires a component of  $\vec{E}$  in the x-direction. Therefore, the wave in the dielectric should be TM mode. Thus, for TM modes where  $H_x=0$  and  $E_x$  exist, the wave equation for  $E_x$  is:

$$(\nabla_{i}^{2} + \{\omega^{2}\mu\varepsilon - \mathbf{k}^{2}\})E_{\mathbf{x}} = 0$$
 (5)

When the condition that  $H_X=0$  is applied to Equations 1, 2, 3 and 4, the result is

$$H_{Y} = \frac{i\omega\varepsilon}{\omega^{2}u\varepsilon - k^{2}} \frac{\partial E_{X}}{\partial z}$$
 (6)

$$E_{z} = \frac{-ik}{\omega^{2} + E - k^{2}} \frac{\partial E_{x}}{\partial z}$$
 (7)

$$E_{Y} = \frac{-ik}{\omega^{2}u\varepsilon - k^{2}} \frac{\partial E_{X}}{\partial V}$$
 (8)

$$H_{z} = \frac{-i\omega\varepsilon}{\omega^{2}u\varepsilon - k^{2}} \frac{\partial E_{x}}{\partial v}$$
 (9)

For simplicity, let

$$\omega^2 \mathbf{u}_0 \, \varepsilon_0 - \mathbf{k}^2 = -\mathbf{a}^2 \tag{10}$$

for waves propagating in vacuum and let

$$\omega^2 \mu_0 \varepsilon - k^2 = b^2 \tag{11}$$

for waves propagating in the dielectric. Assuming no y dependence, which is appropriate for a slab which extends to infinity in the + and - y directions, Eq. 5 reduces to

$$\frac{\partial^2 E}{\partial x^2} + (\omega^2 \mu \varepsilon - k^2) E_{x} = 0$$
 (12)

Thus, in vacuum, substituting Eq. 10 into Eq. 12 yields

$$\frac{\partial^2 E_x}{\partial z^2} - a^2 E_x = 0 \tag{13}$$

which, when the restriction that  $\mathbf{E}_{\mathbf{x}}$  goes to zero as z goes infinity is applied, has as its solution

$$E_{x} = Ae^{-az}$$
 (14)

Similarly, substituting Eq. 11 into Eq. 12 for the dielectric case yields

$$\frac{\partial^2 E_x}{\partial z^2} + b^2 E_x = 0 \tag{15}$$

When the boundary condition of a conductor at the origin is imposed, the solution to Eq. 15 is

$$E_{x} = B \sin (bz) \tag{16}$$

At the vacuum-dielectric interface, the usual boundary conditions apply. That is, the tangential components of  $\vec{E}$  and  $\vec{H}$  must be continuous and the normal components of  $\vec{D}$  and  $\vec{B}$  must also be continuous. For this problem, with the given coordinate system, the tangential components of  $\vec{E}$  are  $E_x$  and  $E_y$ , the tangential components of  $\vec{H}$  are  $H_x$  and  $H_y$ . The normal component of  $\vec{D}=\epsilon\vec{E}$  is  $\epsilon E_z$  and the normal component of  $\vec{B}=(1/\mu)\vec{H}$  is  $\frac{1}{\mu}H_z$ .  $E_y$  and  $H_y$  are zero when the assumption of no y dependence is applied to Eqs. 8 and 9 and for TM modes  $H_x$  is zero by definition. Thus, the boundary conditions reduce to:  $E_x$ ,  $H_y$  and  $\epsilon E_z$  must all be continuous at the

vacuum-dielectric interface. Equating Eqs. 14 and 16 at z=h and applying the boundary condition of continuity to  $E_{\chi}$  leads to

$$Ae^{-ah} = B \sin (bh)$$
 (17)

Making the appropriate substitutions into either Eqs. 6 or 7 and applying the continuity requirement for  $\epsilon E_z$  at z=h results in the same equation.

$$\frac{i\omega\varepsilon_0 \left(-aAe^{-ah}\right)}{-a^2} = \frac{i\omega\varepsilon \left(bB \cos\{bh\}\right)}{b^2} \tag{18}$$

This reduces to

$$\frac{\varepsilon_0 A e^{-ah}}{a} = \frac{\varepsilon B \cos(bh)}{b} \tag{19}$$

Equations 17 and 19 comprise a coupled set of equations which must be simultaneously satisfied.

The following development indicates one method of solution which leads to an expression for the propagation constant, k, and the corresponding phase velocity for the propagating mode. Dividing Eq. 17 by Eq. 19 gives

$$\frac{a}{\varepsilon_0} = \frac{b}{\varepsilon} \tan (bh) \tag{20}$$

$$\frac{\varepsilon}{\varepsilon_0} a = b \tan (bh) \tag{21}$$

$$\frac{\varepsilon}{\varepsilon_0}$$
 ah = bh tan (bh) (22)

Let y=ah and x=bh

$$y = \frac{\varepsilon_0}{\varepsilon} x \tan x \tag{23}$$

Applying the definition of the index of refraction (n)

$$y = \frac{x \tan x}{n^2} \tag{24}$$

Recalling the definitions of a<sup>2</sup> and b<sup>2</sup> and adding them

$$a^2 + b^2 = \omega^2 \mu_0 (\varepsilon - \varepsilon_0)$$
 (25)

$$a^2h^2 + b^2h^2 = \omega^2\mu_0(\varepsilon - \varepsilon_0)h^2$$
 (26)

Substituting for (ah) 2 and (bh) 2

$$y^2 + x^2 = \omega^2 \mu_0 (\varepsilon - \varepsilon_0) h^2$$
 (27)

The right hand side of Eq. 26 is a constant, which we will call  $\mathbb{R}^2$ 

$$y^2 + x^2 = R^2 \tag{28}$$

The simultaneous solution of Eqs. 23 and 28 for a given frequency will result in the value of k which yields fields satisfying all boundary conditions. A representative solution of this system of equations with n=1.461 (polyethylene) is shown in Figure 2.


Although the TM modes are the desired modes, it is necessary to also consider the TE modes to see if there is any degeneracy. Equations 1, 2, 3 and 4 reduce to

$$H_{y} = \frac{-ik}{\omega^{2} \mu \epsilon - k^{2}} \frac{\partial H_{x}}{\partial y}$$
 (29)

$$E_{z} = \frac{i\omega\mu}{\omega^{2}\omega\varepsilon - k^{2}} \frac{\partial H_{x}}{\partial y}$$
 (30)

$$E_{Y} = \frac{-i\omega\mu}{\omega^{2}u\varepsilon - k^{2}} \frac{\partial H_{X}}{\partial z}$$
 (31)

$$H_{z} = \frac{-ik}{\omega^{2} + \kappa^{2}} \frac{\partial H_{x}}{\partial z}$$
 (32)



GRAPHICAL SOLUTION

FIGURE 2.

The TE mode wave equation for  $H_{\mathbf{x}}$  is

$$(\nabla_{\perp}^{2} + \{\omega^{2}\mu\varepsilon - \mathbf{k}^{2}\})\mathbf{H}_{\mathbf{x}} = 0$$
 (33)

Again, assuming no y dependence, Eq. 33 becomes

$$\frac{\partial^2 H_X}{\partial z^2} + (\omega^2 \mu \varepsilon - k^2) H_X = 0$$
 (34)

Substituting Eq. 10 into Eq. 34 for waves propagating in vacuum

$$\frac{\partial^2 H_X}{\partial z^2} - a^2 H_X = 0 \tag{35}$$

which has a solution

$$H_{x} = Ce^{-az}$$
 (36)

and substituting Eq. 11 into Eq. 34 for waves is the dielectric

$$\frac{\partial^2 H}{\partial z^2} + b^2 H_x = 0 \tag{37}$$

which has a solution

$$H_{x} = D \sin (bz) \tag{38}$$

when the appropriate boundary condition at z=0 is imposed.

The same requirements for the vacuum-dielectric interface apply. The assumption of no y dependence immediately makes Eqs. 29 and 30 zero. The remaining tangential component of  $\vec{H}$  is  $H_X$ , the remaining tangential component of  $\vec{E}$  is  $E_X$  and for the normal components of  $\vec{D}$  and  $\vec{B}$ , only  $B_Z = \frac{1}{\mu}H_Z$  remains. These three components must be continuous at the interface

at z=h. Thus

$$Ce^{-ah} = D \sin (bh)$$
 (39)

and

$$\frac{-i\omega\mu_0 \ (-aCe^{-ah})}{-a^2} = \frac{-i\omega\mu_0 \ (bD \cos \{bh\})}{b^2}$$
 (40)

$$\frac{Ce^{-ah}}{a} = \frac{D \cos (bh)}{b} \tag{41}$$

Dividing Eq. 39 by Eq. 41,

$$a = b \tan (bh) \tag{42}$$

$$ah = bh tan (bh)$$
 (43)

Again. letting y=ah and x=bh,

$$y = x \tan x \tag{44}$$

Equations 27 and 28 are still valid and the simultaneous solution of Eqs. 28 and 44 will satisfy all boundary conditions for a given frequency.

The simularity between Eq. 44 and Eq. 23 indicates that both TE and TM modes will propagate at about the same frequency in the dielectric. However, only the TM mode is capable of gaining energy from the electrons. Accordingly, if stimulated Cerenkov radiation is observed, it will be the TM modes that are excited. If, however, an attempt is made to amplify waves fed into the dielectric from some outside source, some mechanism must be found to exclude the TE mode waves from being introduced into the dielectric.

A clearer picture of the relationships can be seen by use of geometry. First, define

$$k_f^2 = \omega^2 \mu_0 \varepsilon_0 \tag{45}$$

the magnitude of the free space k vector for a plane wave and

$$k_{\rm d}^2 = \omega^2 \mu_0 \varepsilon \tag{46}$$

the magnitude of the k vector for a plane wave in the dielectric. Substituting these into Eqs. 10 and 11, the defining equations for  $a^2$  and  $b^2$  respectively, yields after multiplication by  $h^2$ ,

$$k_f^2 h^2 - k^2 h^2 = -a^2 h^2$$
 (47)

$$k_d^2 h^2 - k^2 h^2 = b^2 h^2$$
 (48)

Subtracting Eq. 47 from Eq. 48

$$R^2 = h^2 k_d^2 - h^2 k_f^2$$
 (49)

or

$$R^2 + h^2 k_f^2 = h^2 k_d^2 (50)$$

This defines a right triangle as shown in Figure 2. Rearranging the terms in Eq. 47 defines another right triangle,

$$a^2h^2 + k_f^2h^2 = k^2h^2$$
 (51)

also shown in Figure 3. Note that the side  $k_{\rm f}h$  is common to both triangles and that the magnitude of the unknown k, the wave number of the propagating mode in the dielectric that satisfies all the boundary conditions, is between  $k_{\rm f}$  and  $k_{\rm d}$ . There is an important consequence of this development.

GEOMETRIC RELATIONSHIPS

FIGURE 3.

Since, for energy exchange, the phase velocity of the wave in the dielectric, as represented by the unknown, k, must be matched to the velocity of the electrons. Also the velocity of the electrons must be less than the speed of light in the medium above the dielectric. Thus the region above the dielectric must be in vacuum because 100 MeV electrons have a velocity slightly faster than the velocity of a plane wave in air under normal conditions.

At this point it is possible to proceed to a numerical solution. First, by phase matching the velocity of the electrons to the velocity of the stimulated wave in the dielectric

$$v_{el} = v_{mode}$$
 (52)

By definition

$$\beta = \frac{V}{C} \tag{53}$$

and after applying Eq. 52

$$\beta c = v_{\text{mode}}$$
 (54)

Again, by definition

$$k_{\text{mode}} = \frac{\omega}{v_{\text{mode}}}$$
 (55)

$$k_{\text{mode}} = \frac{\omega}{\beta c}$$
 (56)

and

$$\gamma^2 = \frac{1}{1 - \beta^2} \tag{57}$$

$$\beta^2 = \left(1 - \frac{1}{\gamma^2}\right) \tag{58}$$

Substituting Eq. 58 into Eq. 56

$$k_{\text{mode}} = \frac{\omega}{(1 - \frac{1}{\gamma^2})^{\frac{1}{2}C}}$$
 (59)

Thus,  $k_{mode}$  is determined for a given  $\gamma$  and  $\omega$ . Once  $\omega$  is specified, Eqs. 45 and 46 specify  $k_f$  and  $k_d$ . Rearranging Eq. 10 and substituting Eq. 45 yields

$$a^2 = k_{\text{mode}}^2 - k_{\text{f}}^2 \tag{60}$$

$$a = (k_{\text{mode}}^2 - k_{\text{f}}^2)^{\frac{1}{2}}$$
 (61)

Similarly

$$b^2 = (k_d^2 - k_{mode}^2)$$
 (62)

$$b = (k_d^2 - k_{mode}^2)^{\frac{1}{2}}$$
 (63)

Solving Eq. 21 for h

$$\frac{\varepsilon a}{\varepsilon_0} = b \tan (bh) \tag{21}$$

$$\frac{\varepsilon a}{\varepsilon_0 b} = \tan (bh) \tag{64}$$

$$bh = tan^{-1} \left(n^2 \frac{a}{b}\right) \tag{65}$$

$$h = \frac{1}{b} \tan^{-1} (n^2 \frac{a}{b})$$
 (66)

Thus, given a desired frequency,  $\omega$ , the index of refraction of the dielectric, n, and the energy of the electrons,  $\gamma$ , the thickness of the dielectric can be determined.

The substitution of Eq. 59 into Eqs. 10 and 11 allows the factoring out of  $\omega^2$  and Eq. 66 becomes

$$h = \frac{1}{\omega \left( \frac{1}{(1 - \frac{1}{\gamma^2}) c^2} - \frac{1}{(1 - \frac{1}{\gamma^2}) c^2} \right)^{\frac{1}{2}}} tan^{-1} \left\{ n^2 \frac{\left( \frac{1}{(1 - \frac{1}{\gamma^2}) c^2} - \mu_0 \varepsilon \right)^{\frac{1}{2}}}{\left( \mu_0 \varepsilon - \frac{1}{(1 - \frac{1}{\gamma^2}) c^2} \right)^{\frac{1}{2}}} \right\} (67)$$

which can be solved for  $\omega$  given h, n, and  $\gamma$ .

$$\omega = \frac{1}{h^{(1-\frac{1}{\gamma^2})c^2}} \tan^{-1} \left\{ n^2 \frac{\left(\frac{1}{1-\frac{1}{\gamma^2})c^2} - \mu_0 \epsilon\right)^{\frac{1}{2}}}{\left(1-\frac{1}{\gamma^2})c^2\right)^{\frac{1}{2}}} \right\} (68)$$

The significance of Eq. 68 is that the physical parameters of h, n, and  $\gamma$  specify  $\omega$ . With the proper selection of these parameters, EM radiation of any frequency can be generated.

Examination of Figure 2 readily shows that if the dimensionless parameter bh exceeds  $\pi$ , more than one solution is possible. However, these modes will be at different frequencies and the graphical solution indicates that, if  $x<3\pi$ , the single desired frequency can be extracted by use of a bandpass or high pass filter.

### III. EXPERIMENTAL EQUIPMENT AND PROCEDURE

It was decided to conduct this experiment in the X-band (8-12 GHz) after consulting with Professor Knorr and investigating the availability of the necessary equipment and measuring devices needed to support the experiment. The dielectric chosen was polyethelyne which has an index of refraction of 1.461 [Ref. 2]. The Naval Postgraduate School's Linear Accelerator (LINAC) is capable of producing relativistic electrons with energies up to 120 MeV. The operating characteristics of the NPS LINAC can be found in Appendix A.

A TI-59 programmable calculator program was developed to solve Eqs. 67 and 68. An explanation of this program and a listing of it can be found in Appendix B. Table I shows the input parameter values and the program's solution of Eq. 66 for the 0, 1 and 2 modes.

TABLE I
THICKNESSES OF POLYETHELYNE FOR MODES 0,1,2

m	E [MeV]	n	f [FHz]	h[mm] <sup>1</sup>
0	50	1.461	10	.095
1	50	1.461	10	14.07
2	50	1.461	10	28.15

<sup>1</sup> Program output value

Based on these results, a thickness of 12.7mm (0.5 in) was selected. The values of E=50 MeV, n=1.461, h=12.7mm for a Mode 1 solution predict a frequency of 11.08 GHz when the TI-59 program solves Eq. 68.

The beam of the LINAC is approximately 1 cm in diameter. The width of the dielectric was made to be 5.08 cm to approximate the infinite slab in the y direction. The end of the dielectric away from the LINAC exit window was tapered to fit into an X-band hollow waveguide and to facilitate the TM to TE transition required since a TE mode is the lowest mode that will propagate in a hallow waveguide. Figure 4 is a photograph of the dielectric resonator as it was originally configured.

The first attempt to observe the desired EM radiation met with only limited success. The dielectric slab was mounted about 1 cm below the centerline axis of the LINAC exit window in air. The metal waveguide was sloped slightly to allow clear passage of the electrons over the top of the flange connector to the detector. A diode detector was used with its output lead to an oscilliscope (CRO). With a beam energy of 53.85 MeV and an average beam current of 8.0 nAmp, the CRO display showed a pulse of about 1 usec with strength varying from 100-200 mV as the beam was tuned, focused and

<sup>&</sup>lt;sup>2</sup>All currents read on a secondary emission monitor with 6% efficiency, and the monitor current is reported in this work.



DIELECTRIC RESONATOR


FIGURE 4.

varied in distance from the slab. However, attempts to measure the frequency with a high Q calibrated cavity resonator were unsuccessful.

To determine if the observed pulse was caused by the dielectric, the slab was removed leaving the hollow waveguide in place. When the beam was turned on, a 0.5 microsecond pulse of slightly reduced magnitude was observed. At this point, it was realized that the observed pulse might be caused by Cerenkov radiation in air. Although commonly accepted as 1.0, the actual index of refraction of standard dry air is 1.003 [Ref. 3]. Using this value as  $\beta^{-1}$  it can be easily shown that electrons with energies exceeding 20.856 MeV will exceed the speed of light in standard dry air. Thus, electrons above that energy would exceed the velocity of a plane wave in air, and could not be matched to the TM mode velocity.

A simple experiment was designed to investigate this possibility. The equipment arrangement is shown in Figure 5. The reflector used was a thin sheet of aluminum which would allow the passage of the electrons and reflect any EM radiation. With the reflector in place, a pulse was observed from detector 2 whose magnitude was approximately 0.5 times the magnitude of the output from detector 1. When the reflector was removed, a pulse of magnitude 0.1 times the output of

<sup>3</sup>See Section II.




AIR CERENKOV EXPERIMENTAL SETUP

FIGURE 5.

detector 1 was observed from detector 2. These results support the hypothesis of air Cerenkov. Since the air Cerenkov should be very broadband, no attempt was made at this time to measure the frequency of this radiation.

Based on these results, it was decided to enclose the dielectric slab in a vacuum chamber. Figure 6 is a photograph of the interior of the vacuum chamber. The vacuum was maintained in the chamber by installing a 1/16 in. thick piece of polyethelyne between two waveguide flanges exterior to the chamber. A waveguide run of about 75 ft. was added to the setup which allowed for the positioning of the detector in the LINAC control room thus eliminating the long, lossy coaxial cable runs. A Tektronic 491 Spectrum Analyzer (491-5/A) obtained to facilitate frequency analysis.

The use c. this new setup with team energy of 100.97 MeV, beam current of 4.3 nA and the same diode detector used before resulted in a 0.5 Volt peak pulse of about 1 microsecond duration. The increase in peak output was attributed to the reduction in line loss provided by the replacement of the coax cable by waveguide. Subsequent tests, which will be discussed later, have modified this hypothesis. The 491-S/A, with a 20 dB attenuator inserted between the waveguide to coax adapter and the S/A, detected signals at 12.39 GHz and 8.57 GHz. The 12.39 GHz signal was the image of a real signal above the frequency range of the 491-S/A. Using a relatively low Q cavity, it was determined that most of the



VACUUM CHAMBER

FIGURE 6.


power in the pulse was in the 8.57 GHz signal. A dispersive high pass filter with a cutoff frequency of 9.9 GHz was installed between the waveguide from the dielectric and the coax adapter. With this arrangement and no attenuation at the input of the 491-S/A, valid signals were detected at 8.58, 8.99 and 11.42 GHz. When the dielectric was removed from the vacuum chamber and the test repeated, the same signals were detected. Both with and without dielectric, all signals disappeared when electron injection was interrupted with LINAC RF power maintained.

The 8.57 GHz and 11.48 GHz signals appear to be the third and fourth harmonics of the LINAC operating frequency. The exact cause of the 8.99 GHz signal is not known but it is believed to be caused by a resonant mode of the vacuum chamber. The chamber is a rectangular aluminum box with 10 mil aluminum windows for electron entry and exit and as such would act as a cavity resonator. Equipment limitations prevent the measurement of any change in strength of the 11.48 GHz signal with and without the dielectric slab in place. This frequency is only 4% above the predicted frequency for the given parameters and it is possible that the desired signal is hidden by the LINAC harmonic at that frequency. Also, the actual index of refraction of the polyethylene was not experimentally determined and it was not manufactured specifically for optical use. It is possible that a slight change in n and/or inhomogeneities in the material could cause some frequency shifting.

Additional tests were conducted with this configuration. Two anomalies were observed which required further explanation. First, an intermittent, valid signal was detected at 10.24 GHz. This signal is not fully understood but it is believed to be extraneous to the experiment. Secondly, the peak output of the diode detector varied as much as an order of magnitude with the same beam parameters and beam position.

This observation led to a more intensive investigation of the TM to TE coupling at the dielectric/waveguide transition. In particular, for the m=1 mode, it was realized that cancellation of the E-field could occur at the transition point. A graphical representation of the E-field in the dielectric is shown in Figure 7. It was decided to nullify the lower field at the transition by inserting a vertical conductor into the dielectric slab at the mouth of the waveguide as shown in Figure 8. The vertical conductor should not affect any TE modes propagating in the dielectric but should nullify the cancellation effect of the m=1 mode for any TM mode waves propagating in the dielectric. Another modification of the setup was also made at this time. 10 mil. aluminum window between the LINAC and the vacuum chamber was replaced by a 10 mil. mylar window to minimize beam spreading at the entrance to the vacuum chamber.

Table II shows the results of the frequency analysis of the dielectric with and without the conductor in place. The beam parameters were as follows: E=65.29 MeV, I=4.0 nA.



E-FIELD IN THE DIELECTRIC

FIGURE 7.




TABLE II
FREQUENCIES OBSERVED

With Conductor		Without (	Without Conductor	
f [GH2]	Strength	f [GHz]	Strength	
8.57	very strong	8.57	strong	
9.00	moderate	9.00	weak	
9.52	weak			
10.21	moderate	10.25	moderate	
10.92	weak			
11.42	strong	11.50	moderate	

The peak voltage observed from the diode detector was 150 mV without the vertical conductor and 100 mV with the conductor in place. It is interesting to note that although half of the area of the waveguide was blocked, the detector voltage dropped by only about one third.

For input values of E=65.29 MeV, n=1.461, h=12.7 mm and m=1, the TI-59 program predicts a frequency of 11.08 GHz.

The 9.52 GHz signal does not correspond to any predicted frequency. Possible explanations of this frequency will be discussed later. The observed 10.92 GHz signal is only 1.4% below the predicted value. Since this frequency is only observed when the vertical conductor is in place, it is believed that this is a TM mode resulting from stimulated Cerenkov radiation.

## IV. DISCUSSION AND CONCLUSIONS

It appears from the foregoing experiment that stimulated Cerenkov radiation can be produced at the predicted frequency with the proper choice of parameters. The 1.4% error can be explained in several ways. First, the predicted frequency is based on an algorithm that provides an approximate solution for modes where m>0. Second, nonoptical quality polyethylene was used for the dielectric slab. Finally, the theoretical development assumed an infinite slab in the y direction. In fact, a finite slab was used whose y dimension was about 5 times the diameter of the focused beam. Any one of the deviations from the ideal case or a combination of them could account for the error. The most probable source of error is the index of refraction of the polyethylene. An index of refraction of 1.473, a change of 0.012 which is less than 1% of the tabulated value in Ref. 3, would reduce the error to essentially zero.

The cause of the TM mode frequency at 9.52 GHz shown in Table II is not fully understood. It could be a result of the edge effects caused by the finite width of the dielectric or it might be a resonant TM mode of the vacuum chamber.

A secondary effect observed during the course of this experiment is worth noting. When the focused beam was passed above the dielectric, the output of the diode detector

varied with the beam current. This effect was present both in air and in vacuum. It may be possible to construct a calibration curve of diode voltage vs. beam current and thereby develop a beam current measuring device which does not destroy the beam downstream from the measurement point as the beam current measuring device presently in use does.

It is readily apparent from the magnitude of the diode pulse that the stimulated Cerenkov radiation effect is very inefficient. To match the mode with high speed electrons requires that the component of the mode's E-field parallel to the electron beam be small compared with the field's transverse components. This will tend to make the coupling small. The output power of the diode detector is less than 0.5 mWatts. Most of this power, conservatively estimated at 95%, is in the 8.57 GHz signal as demonstrated in Section III. This does, however, enhance the possibility of developing an electron beam current meter, based on this process, which has only a minimal effect on the beam itself.

The results of this experiment support the hypothesis that stimulated Cerenkov radiation can be produced at a frequency specified by the physical parameters of electron energy, index of refraction and dielectric thickness. It appears that the wave-electron coupling is a weak effect which is further degraded by the TM to TE coupling used to extract the signal in this experiment. Greater efficiency may be possible if a more effective means of extracting the

signal is developed. The signal itself may be increased in strength by lengthening the dielectric slab to increase the length of the wave-electron interaction region.

Additional work in the area of stimulated Cerenkov radiation appears to be warranted. The development presented here is not guaranteed to be unique. There may be other modes that can be stimulated in the dielectric, one of which might provide a stronger signal. A mode with a larger longitudinal component could increase the electron-mode coupling. Additionally, the effect of the pulsed beam of electrons should be studied in depth. Specifically, the question of why this experimental setup produces most of its output power at the third harmonic of the LINAC operating frequency should be investigated in greater detail. If the power in the LINAC harmonics can be shifted to the Cerenkov frequency it would greatly increase the usefulness of the stimulated Cerenkov process as a radiation source. Finally, generation of X-band radiation using the m=0 mode should be attempted as a preliminary step in extending this work into the IR range. The dielectric thickness predicted by the theoretical development presented here for an IR generator is of the order of microns. The X-band m=0 thickness is in this range. Extracting a signal from a dielectric this thin may cause some difficulties. The experience thus gained should be valuable in extending this work into the IR range.

## APPENDIX A

## LINAC OPERATING CHARACTERISTICS

Max Energy 120 MeV

Max Average Current 3-5 microAmp

Operating Frequency 2.856 GHz

PRF 60 pps

Pulse Duration 1.0 microseconds

Nr. of Klystrons 3

Peak Output Power per Klystron 21 MWatts

#### APPENDIX B

#### TI-59 PROGRAM LISTING AND EXPLANATION

This program does not use any library programs within the algorithm. The inputs are the electron beam energy (in MeV), the index of refraction of the dielectric (dimensionless), either the desired frequency (in Hz) or the dielectric thickness (in meters), and the mode (dimensionless). The mode input determines which leg of the  $y=(1/n^2)x$  tan x in the curve (in the first quadrant) is used. For a given m=0,1,2... the solution is found for x values such that x=0,1,2... the solution is found for x=0,1,2... as noted in Chapter II, if  $x>\pi$ , more than one solution is possible. This program solves only for the solution in the x=0,1,2... the matrix x=0,1,2... the solution in the matrix x=0,1,2... the solut

The solution for m=0 is unique and exact. Solutions for higher order modes are found using an iterative search. The solution is approximate in that the program searches down the designated leg of  $y=(1/n^2)x$  tan x in discrete steps until it finds a y value less than the y value for the corresponding m=0 case. This value of y is then taken as the solution point for the input mode.

To solve Equation 67:

- 1. Load program.
- 2. Enter E[MeV], press A.

- 3. Enter n, press B.
- 4. Enter f[nz], press C.
- 5. Enter m, press E.

The program will solve for h [meters].

To solve Equation 68:

- 1. Load program.
- Enter E[MeV], press A.
- 3. Enter n, press B.
- 4. Enter h[m], press D.
- 5. Enter m, press E'.

The program will solve for f[Hz].

The program listing is on the following pages.

```
65 X
                       049
                                              098
                                                   42 STO
000
     76 LBL
                       050
                            89 π
                                              099
001
     11 A
                                                    91 R/S
     57 ENG
                       051
                             95 =
                                              100
002
                       052
                             42 STO
003
     55 ÷
                                              101
                                                    76 LBL
                       053
                             05 05
                                                    18 C7
004
     93 .
                                              102
                       054
                             91 R/S
                                                   01 1
                                              103
005
     05 5
                       055
                             76 LBL
                                                   42 STO
                                              104
006
     01 1
                       056
                             14 D
                                              105
                                                   05 05
007
     01 1
                       057
                             42 STO
                                              106
                                                    71 SBR
800
     95 =
                                              107
009
     42 STO
                       058
                             06 06
                                                    88 DMS
                                                    71 SER
                             91 R/S
010
     00 00
                       059
                                              108
                             76 LBL
011
     91 R/S
                       060
                                              109
                                                    69 OP
                             15 E
42 STO
                                                    55 ÷
                       061
012
     76 LBL
                                              110
     12 B
33 x<sup>2</sup>
                                                    02 2
                       062
                                              111
013
                             07 07
                       063
                                              112
                                                    55 ÷
014
                     065
065
                             67 EQ
                                              113
                                                   89 π
     42 STO
015
                             19 D'
                                              114
                                                   95 =
     01 01
016
     65 X
                      066
                             71 SBR
                                             115
                                                    91 R/S
017
                      067
                             88 DMS
                                             116
                                                   76 LBL
018
     08 8
     93 .
                      068
                             71 SBR
                                              117
                                                    19 D'
019
020
     08 8
                      069
                             68 NOP
                                             118
                                                    71 SBR
                                            119
120
                                                   88 DMS
                       070
021
     05 5
                             43 RCL
                       071
                                                   71 SBR
022
     04 4
                             13 13
                       072
                             65 X
                                              121
                                                    68 NOP
     01 1
023
                        073
                                              122
                                                    91 R/S
     01 1
                             43 RCL
024
                        074
                                              123
                                                    76 LBL
025
     08 8
                             11 11
     52 EE
                        075
                             95 =
                                              124
                                                    10 E'
026
                             42 STO
                                                    42 STO
     94 +/-
                        076
                                              125
027
                             14 14
71 SBR
58 FIX
                                                   07 07
                        077
028
     01 1
                                               126
                                                   67 EQ
                        078
                                              127
029
     02 2
                        079
                                                   18 C'
     42 STO
                                              128
030
                             42 RCL
     02 02
                        080
                                              129
                                                   01 1
031
                             15 15
33 x<sup>2</sup>
     95 =
                        081
                                              130
                                                   42 STO
032
                       082
                                              131
                                                   05 05
033
     42 STO
                             85 +
                        083
                                              132
                                                   71 SBR
034
     03 03
                                                   88 DMS
     04 4
                       084
                             43 RCL
                                              133
035
                        085 17 17
                                                   71 SBR
     52 EE
                                              134
036
                             33 x^2
                                              135
                                                   69 OP
                        086
037
     94 +/-
     07 7
                        087
                             95 =
                                              136
                                                    43 RCL
038
                        088 55 ÷
                                              137
                                                    08 08
039
     65 X
                        089
                             53 (
                                              138
                                                    75 -
040
     89 π
                        090 43 RCL
091 10 10
                                              139
                                                    43 RCL
041
     95 =
                                               140
                                                    09 09
042
     42 STO
                        092
                                                    95 =
043
     04 04
                             75 -
                                               141
                                                    34 √x
                                              142
                        093
                             43 RCL
044
     91 R/S
                            09 09
                        094
                                              143
                                                    65 X
045
     76 LBL
                             54 )
95 =
                        095
                                              144
                                                    43 RCL
046
     13 C
     65 X
                        096
                                              145
                                                    19 19
047
                              34 √x
     02 2
                       097
                                               146
                                                    65 X
048
```

```
245
                                                         34 √x
                                93 .
                          196
     43 RCL
147
                                                         42 STO
                                09 9
                                                   246
                          197
     06 06
148
                                09 9
                                                   247
                                                         11 11
                          198
149
     95 =
                                                   248
                                                         43 RCL
                          199
                                07 7
     42 STO
150
                                                         10 10
                                                   249
                          200
                                09 9
151
     14 14
                                                         75 -
                                                   250
                          201
                                02 2
152
     71 SBR
                                                   251
                                                         43 RCL
                                05 5
                           202
     58 FIX
153
                                                   252
                                                         08 08
                                52 EE
     43 RCL
                           203
154
                                08 8
33 x<sup>2</sup>
                                                   253
                                                         95 =
                           204
     15 15
155
                                                         34 √x
                                                   254
                           205
156
     33 x^2
                                                   255
                                                         42 STO
                                95 =
                           206
      85 +
157
                                                         12 12
                                                   256
                                35 1/x
                           207
158
      43 RCL
                                                   257
                                                         92 RTN
                                 65 X
      17 17
33 x<sup>2</sup>
                           208
159
                                                   258
259
                                                         76 LBL
                                 43 RCL
                           209
160
                                                         68 NOP
                                05 05
33 x<sup>2</sup>
                           210
      95 =
161
                                                   260
                                                         43 RCL
                           211
      55 ÷
162
                                95 -
                                                   261
                                                         01 01
                           212
163
      43 RCL
                                                   262
                                42 STO
08 08
                                                         65 X
                           213
164
      06 06
                                                   263
                                                         43 RCL
      33 \times^2
                           214
165
                                                         11 11
                                                   264
                                43 RCL
                           215
166
      55 ÷
                                05 05
33 x<sup>2</sup>
                                                         55 ÷
                                                   265
                           216
167
      53 (
                                                   266
                                                         43 RCL
                           217
168
      43 RCL
                                 65 X
                                                   267
                                                         12 12
                           218
169
      10 10
                                                   268
                                                         95 =
                                43 RCL
                           219
170
      75 -
                                                    269
                                                          70 RAD
                                02 02
                           220
      43 RCL
171
                                                          22 INV
                                                    270
                           221
                                65 X
172
      09 09
                                                          30 TAN
                                                    271
                           222
                                43 RCL
173
      54)
                                                    272
                                                          55 ÷
                           223
                                04 04
      95 =_
174
                                                    273
                                                          43 RCL
      34 √x
                           224
                                95 =
175
                                                    274
                                                          12 12
                                 42 STO
                           225
      42 STO
176
                           226
227
228
                                                    275
                                                          95 =
                                09 09
      20 20
 177
                                                          42 STO
                                 43 RCL
                                                    276
 178
      55 ÷
                                                          13 13
                                05 05
33 x<sup>2</sup>
                                                    277
 179
      02 2
                                                    278
                                                          92 RTN
                           229
      55 ÷
 180
                                 65 X
                                                          76 LBL
                                                    279
                           230
 181
       89 π
                                                    280
                                                          69 OP
                                 43 RCL
                           231
       95 =
 182
                                                          43 RCL
                                                    281
                           232
                                 03 03
       91 R/S
 183
                                                          01 01
                           233
                                                    282
                                 65 X
       76 LBL
 184
                                                          65 X
                                                    283
                                 43 RCL
                            234
       88 DMS
 185
                                                          43 RCL
                                                    284
                            235
                                 04 04
       43 RCL
 186
                                                          11 11
                                                    285
                            236
                                 95 =
       00 00
33 x<sup>2</sup>
 187
                                                    286
                                                          55 ÷
                                  42 STO
                            237
 188
                                                          43 RCL
                                                    287
                            238
                                 10 10
       35 1/x
 189
                                                          12 12
                            239
                                                    288
                                 43 RCL
 190
      94 +/-
                                                    289
                                                          95 =
                            240
                                 08 08
 191
       85 +
                                                          70 RAD
                                                    290
                                  75 -
                            241
 192
       01 1
                                                    291
                                                          22 INV
                            242
                                  43 RCL
 193
       95 =
                                                          30 TAN
                                                     292
                                  09 09
                            243
       65 X
 194
                                                          55 ÷
                                                     293
                            244
                                  95 =
 195
       02 2
```

```
294
     53 (
     43 RCL
295
     12 12
296
     65 X
297
     43 RCL
298
     06 06
299
300
     54 )
     95 =
301
      42 STO
302
      19 19
303
304
      92 RTN
      76 LBL
205
      58 FIX
 306
      09 9
 207
      94 +/-
 308
      22 INV
 309
      28 LOG
 310
      85 +
 311
      43 RCL
 312
 313
      07 07
       65 X
 314
       89 π
 315
       95 =
 316
       42 STO
 317
       15 15
 318
  319
       01 1
       01 1
  320
       94 +/-
  321
       22 INV
  322
       28 LOG
  232
        94 +/-
  324
        42 STO
  325
        16 16
  326
        76 LBL
  327
        50 |x|
  328
        43 RCL
  329
        15 15
70 RAD
   330
   331
        30 TAN
   332
        65 X
   333
        43 RCL
   334
        15 15
   335
         55 ÷
   336
         43 RCL
   337
         01 01
   338
         95 =
   339
         42 STO
17 17
    340
   341
         75 -
    342
```

### LIST OF REFERENCES

- 1. Walsh, J. E., "Stimulated Cerenkov Radiation," Physics of Quantum Electronics, Vol. 5, Ed. S. F. Jacobs et al, Addison Wesley Publishing Company, Inc., 1978.
- 2. Simonis, G. J., "Near mm Wave Materials," Harry Diamond Labs.
- 3. Hodgman, C. D., Handbook of Chemistry and Physics, 38th Edition, Chemical Rubber Publishing Co., 1956.

# INITIAL DISTRIBUTION LIST

		No. Copies
1.	Defense Technical Information Center Cameron Station Alexandria, Virginia 22314	2
2.	Library, Code 0142 Naval Postgraduate School Monterey, California 93940	2
3.	Physics Library, Code 61 Department of Physics and Chemistry Naval Postgraduate School Monterey, California 93940	1
4.	Professor F. R. Buskirk, Code 61Bs Department of Physics and Chemistry Naval Postgraduate School Monterey, California 93940	5
5.	LCDR David E. McLaughlin, USN 1062 Clearspring Lane Virginia Beach, Virginia 23464	1